# RM35JA31MW

Harmony, Modular 1-phase current control relay, 5 A, 2 CO, 2...500 mA, , 24...240 V AC/DC



#### Main

Range of Product	Harmony Control Relays
Product or Component Type	Current control relay
Relay Type	Current control relay
Relay name	RM35JA
Relay monitored parameters	Overcurrent or undercurrent in window mode Overcurrent or undercurrent detection
Time delay	Adjustable 120 s, 0 + 10 % on energisation Ti Adjustable 0.330 s, 0 + 10 % on crossing the threshold Tt
Switching capacity in VA	1250 VA
Minimum switching current	10 mA 5 V DC
Maximum switching current	5 A AC
Maximum power consumption in VA	3.5 VA AC
Measurement range	10100 mA E2-M terminals 220 mA E1-M terminals 2500 mA current 50500 mA E3-M terminals
Utilisation category	AC-12 IEC 60947-5-1 AC-13 IEC 60947-5-1 AC-14 IEC 60947-5-1 AC-15 IEC 60947-5-1 DC-12 IEC 60947-5-1 DC-13 IEC 60947-5-1 DC-14 IEC 60947-5-1
Contacts type and composition	2 C/O

#### Complementary

Complementary		
Reset time	1500 ms time delay	
Maximum switching voltage	250 V AC	
[Us] Rated Supply Voltage	24240 V AC/DC 50/60 Hz +/- 10 %	
Supply voltage limits	20.4264 V AC/DC	
Operating voltage tolerance	- 15 % + 10 % Un	
Maximum power consumption in W	0.6 W DC	
Control circuit frequency	4070 Hz +/- 10 %	
Resistance across terminals	1 Ohm E2-M terminals 5 Ohm E1-M terminals 0.2 Ohm E3-M terminals	
Output contacts	2 C/O	
Nominal output current	5 A	
Maximum measuring cycle	30 ms measurement cycle as true rms value	
Hysteresis	550 % threshold setting	
Delay at power up	0.3 s	
Measurement accuracy	+/- 10 % of the full scale value	
Repeat accuracy	+/- 0.5 % input and measurement circuit +/- 2 % time delay	

Polarity No DC Threshold setting 10100 %	Measurement error	0.05 %/°C with temperature variation	
Threshold setting  10100 %  Marking  CE: EMC 89/336/EEC CE: 73/23/EEC  Overvoltage category  III IEC 60664-1  Insulation resistance  \$ 500 MOhm 500 V DC between supply and relay output IEC 60255-5		1 by volt over the whole range with voltage variation	
Marking CE : EMC 89/336/EEC CE : 73/23/EEC  Overvoltage category III IEC 60664-1  Insulation resistance		117 - 2	
CE: 73/23/EEC  Overvoltage category  III IEC 60664-1  Insulation resistance  > 500 MOhm 500 V DC between supply and relay output IEC 60255-5 > 500 MOhm 500 V DC between measurement and relay output IEC 60664-1 > 1 MOhm 500 V DC between supply and measurement IEC 60255-5 > 500 MOhm 500 V DC between supply and relay output IEC 60664-1 > 1 MOhm 500 V DC between supply and relay output IEC 60664-1 > 500 MOhm 500 V DC between supply and relay output IEC 60255-5 > 500 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 MOhm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply and relay output IEC 60255-5 > 1 Mohm 500 V DC between supply	Threshold setting	10100 %	
Insulation resistance    Source	Marking		
Solo MOhm 500 V DC between supply and measurement 1EC 60265-1	Overvoltage category	III IEC 60664-1	
Operating position  Any position without derating  Connections - terminals  Screw terminals, 1 x 0.51 x 4 mm² AWG 20AWG 11) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG	Insulation resistance	<ul> <li>&gt; 500 MOhm 500 V DC between measurement and relay output IEC 60664-1</li> <li>&gt; 1 MOhm 500 V DC between supply and measurement IEC 60255-5</li> <li>&gt; 500 MOhm 500 V DC between supply and relay output IEC 60664-1</li> <li>&gt; 500 MOhm 500 V DC between measurement and relay output IEC 60255-5</li> </ul>	
Connections - terminals  Screw terminals, 1 x 0.51 x 4 mm² AWG 20AWG 11) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 14) solid without cable end Screw terminals, 1 x 0.51 x 4 mm² AWG 20AWG 11) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 11) solid without cable end Screw terminals, 1 x 0.51 x 4 mm² AWG 20AWG 14) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.51 x 4 mm² AWG 20AWG 14) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.51 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.51	[Ui] rated insulation voltage	250 V IEC 60664-1	
Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 1 x 0.21 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² AWG 24AWG 16) flexible with cable end Screw terminals, 2 x 0.22 mm² AWG 24AWG	Operating position	Any position without derating	
Housing material  Self-extinguishing plastic  Local signalling For power ON LED (green) For relay ON LED (yellow)  Mounting support 35 mm symmetrical DIN rail conforming to EN/IEC 60715  Electrical durability 100000 cycles  Mechanical durability 30000000 cycles  Operating rate <= 360 operations/hour full load  Safety reliability data MTTFd = 296.8 years B10d = 270000  Contacts material  Cadmium free  Width 1.38 in (35 mm)	Connections - terminals	Screw terminals, 2 x 0.52 x 2.5 mm² AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.21 x 2.5 mm² AWG 24AWG 12) flexible with cable end	
Local signalling  For power ON LED (green) For relay ON LED (yellow)  Mounting support  35 mm symmetrical DIN rail conforming to EN/IEC 60715  Electrical durability  100000 cycles  Mechanical durability  30000000 cycles  Operating rate  <= 360 operations/hour full load  Safety reliability data  MTTFd = 296.8 years B10d = 270000  Contacts material  Cadmium free  Width  1.38 in (35 mm)	Tightening torque	5.318.85 lbf.in (0.61 N.m) IEC 60947-1	
For relay ON LED (yellow)  Mounting support 35 mm symmetrical DIN rail conforming to EN/IEC 60715  Electrical durability 100000 cycles  Mechanical durability 30000000 cycles  Operating rate <= 360 operations/hour full load  Safety reliability data MTTFd = 296.8 years B10d = 270000  Contacts material Cadmium free  Width 1.38 in (35 mm)	Housing material	Self-extinguishing plastic	
Electrical durability 100000 cycles  Mechanical durability 30000000 cycles  Operating rate <= 360 operations/hour full load  Safety reliability data MTTFd = 296.8 years B10d = 270000  Contacts material Cadmium free  Width 1.38 in (35 mm)	Local signalling	1 (0 )	
Mechanical durability  3000000 cycles  Operating rate  <= 360 operations/hour full load  MTTFd = 296.8 years B10d = 270000  Contacts material  Cadmium free  Width  1.38 in (35 mm)	Mounting support	35 mm symmetrical DIN rail conforming to EN/IEC 60715	
Operating rate <= 360 operations/hour full load  Safety reliability data MTTFd = 296.8 years B10d = 270000  Contacts material Cadmium free  Width 1.38 in (35 mm)	Electrical durability	100000 cycles	
Safety reliability data  MTTFd = 296.8 years B10d = 270000  Contacts material  Cadmium free  Width  1.38 in (35 mm)	Mechanical durability	30000000 cycles	
B10d = 270000           Contacts material         Cadmium free           Width         1.38 in (35 mm)	Operating rate	<= 360 operations/hour full load	
Width 1.38 in (35 mm)	Safety reliability data	•	
	Contacts material	Cadmium free	
Net Weight 0.29 lb(US) (0.13 kg)	Width	1.38 in (35 mm)	
	Net Weight	0.29 lb(US) (0.13 kg)	

#### Environment

Immunity to microbreaks	50 ms	
Electromagnetic compatibility	Emission standard for industrial environments EN/IEC 61000-6-4 Emission standard for residential, commercial and light-industrial environments EN/IEC 61000-6-3 Immunity for industrial environments NF EN/IEC 61000-6-2	
Standards	EN/IEC 60255-6	
Product Certifications	GL CSA GOST UL C-tick	
Ambient Air Temperature for Storage	-40158 °F (-4070 °C)	
Ambient air temperature for operation	-4122 °F (-2050 °C)	
Relative humidity	95 % 131 °F (55 °C) IEC 60068-2-30	
Vibration resistance	0.35 mm 557.6 Hz)IEC 60068-2-6 1 gn 57.6150 Hz)IEC 60255-21-1	
Shock resistance	15 gn 11 ms IEC 60255-21-1	
IP degree of protection	IP20 IEC 60529 terminals) IP30 IEC 60529 casing)	
Pollution degree	3 IEC 60664-1	
Dielectric test voltage	2 KV AC 50 Hz, 1 min IEC 60255-5 2 kV AC 50 Hz, 1 min IEC 60664-1	
Non-dissipating shock wave	4 KV IEC 60255-5 4 KV IEC 60664-1 4 kV IEC 61000-4-5	

Ordering	and	ship	pino	i deta	ils

Category	22380 - RELAYS-MEASUREMENT (RM17-RM35)
Discount Schedule	CP2
GTIN	3389119405218
Nbr. of units in pkg.	1
Package weight(Lbs)	4.87 oz (138 g)
Returnability	Yes
Country of origin	ID

### Packing Units

<u> </u>	
Unit Type of Package 1	PCE
Package 1 Height	1.77 in (4.5 cm)
Package 1 width	3.07 in (7.8 cm)
Package 1 Length	3.74 in (9.5 cm)
Unit Type of Package 2	S03
Number of Units in Package 2	48
Package 2 Weight	15.97 lb(US) (7.244 kg)
Package 2 Height	11.81 in (30 cm)
Package 2 width	11.81 in (30 cm)
Package 2 Length	15.75 in (40 cm)

### Offer Sustainability

Green Premium product	
WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov	
REACh Declaration	
Pro-active compliance (Product out of EU RoHS legal scope)	
Yes	
€Yes	
China RoHS Declaration	
Product Environmental Profile	
☐ End Of Life Information	
The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.	

#### Contractual warranty


Contractadi Wallanty		
Warranty	18 months	

# Product data sheet Dimensions Drawings

# RM35JA31MW


#### **Current Control Relays**

#### **Dimensions and Mounting**



#### **Current Control Relays**


#### Wiring Diagram




#### **Application Schemes**

#### Example: Detection of Jamming on a Crusher (Overcurrent Function)

#### Current measured ≤ 15 A



#### Current measured > 15 A




# Product data sheet Technical Description

## RM35JA31MW


#### **Function Diagrams**

#### **Undercurrent Detection**

Without memory ("No Memory" mode)




With memory ("Memory" mode)




#### **Overcurrent Detection**

Without memory ("No Memory" mode)



With memory ("Memory" mode)



#### Legend

Ti Starting inhibition time delay

Tt Time delay after crossing of threshold

Un Supply voltage

I Monitored current

H Hysteresis

I> Overcurrent threshold

I< Undercurrent threshold

11-12/11-14, 21-22/21-24 Output relay connections

Relay status: black color = energized.

NOTE: In "Memory" mode, the relay opens when crossing of the threshold is detected and then stays in that position. The power supply voltage must be switched off to reset the product.